



### Description

This amplifier is perfect for less elaborate multizone audio systems and can be mated with any of our surround receivers or our preamp/processor to add music throughout three additional living areas or “zones” of your home. You can also add another RMB-1506 for larger multizone applications that don’t need the power output of the RMB-1512. As with all Rotel multichannel amplifiers it includes all of the most wanted custom installation features.

*\*Note – all Rotel 15 series components may be rack mounted and remotely controlled via RS-232, IR, or 12 volt (depending on model) for complete stealth operation.*

### Specifications

<b>Power Output all channels driven</b>	50 watts x 6ch (20 Hz-20kHz, <0.03% THD, 8 ohms) 100 watts x 6ch (20 Hz-20kHz, <0.03% THD, 4 ohms)	<b>Frequency Response (+/-1 dB)</b>	10Hz-100kHz
<b>IM Distortion</b>	< 0.03%	<b>S/N Ratio (IHF A)</b>	115 dB
<b>Damping Factor (8 ohms)</b>	>200	<b>Power Consumption</b>	450 watts
<b>Gain</b>		<b>Dimensions (W x H x D) mm</b>	431 x 144 x 424 mm (17 x 5 5/8 x 16 5/8 in)
<b>Input Sens. / Impedance</b>	1.0 V / 20 k Ohms	<b>Weight</b>	15.3 kg (33.7 lbs)

[www.rotel.com](http://www.rotel.com)

The Rotel Co. Ltd.  
10-10 Shinsen-Cho  
Shibuya-Ku,  
Tokyo 150, Japan

Rotel of America  
54 Concord St.  
N. Reading, MA 01864  
USA  
T +1 978 664 3820  
F +1 978 664 4109

Rotel Europe  
Dale Road  
Worthing  
West Sussex BN11 2BH, UK  
T +44 (0) 1903 221 763  
F +44 (0) 1903 221 525