

Classé

Omega pre-amplifier



INPUT SELECTOR

STANDBY

Model Omega pre-amplifier

Frequency response ± 0.1 db
Distortion THD+noise 20Hz-20kHz
0.004%

Outputs
Single-ended 2/9/50 Ω
(number/max volts/impedance)
Balanced 2/9/50 Ω
(number/max volts/impedance)

Inputs
Single-ended 3/33K Ω
(number/impedance)
Balanced 3/33K Ω
(number/impedance)

Tape
Input/output 1 single-ended
Input 1 balanced

Power supply
Transformers 2x148VA/1x126VA
(audio/mechanical)
Number of capacitors 49
Total capacitance 176,880 μ F

Weight & measurements
Net weight 9.6kg
21.1lbs
Height 105mm
4.1"
Width 483mm
19"
Depth 387mm
15.25"

Power supply
Net weight 13.4kg
29.5lbs
Height 105mm
4.1"
Width 483mm
19"
Depth 387mm
15.25"

Classé Audio Inc. reserve
the right to amend technical
specifications without further
notice.

USA & Canada
Classé Audio Inc.
5070 Francois Cusson
Lachine
Quebec
Canada
H8T 1B3

Telephone +1 514 636 6384
Facsimile +1 514 636 1428
www.classe.com
cservice@classeaudio.com

Europe
B&W Loudspeakers Ltd
Meadow Road
Worthing BN11 2RX
England

UK
B&W Loudspeakers (UK) Ltd
Marlborough Road
Lancing BN15 8TR

Telephone +44 1903 750750
Facsimile +44 1903 750694
uksales@bwspeakers.com

Hong Kong
B&W Loudspeakers (Asia) Ltd
Flat U, 11F Camelpoint Building
Block 111, 60 Hoi Yuen Road
Kwun Ton, Kowloon
Hong Kong

Telephone +8522 790 8903
Facsimile +8522 341 2777
bwhome@bwspeakerasia.com.hk

Design:
Thomas Manss & Company

PJ08346

