

The Classé SSP-300 / SSP-600 uses RC6 protocol for infrared communications. The following list of infrared codes can be used to program a universal or learning remote control. The Classé Remote Control uses a frequency of 56.0 kHz.

Please refer to your remote control's user manual for information on how to program your remote control.

Sys code	IR code	Action
116	1	Toggle Tape Monitor on/off
116	2	Change input to Line 1 (input 1)
116	3	Change input to Line 2 (input 2)
116	4	Change input to Line 3 (input 3)
116	5	Change input to Line 4 (input 4)
116	6	Change input to Line 5 (input 5)
116	7	Change input to Line 6 (input 6)
116	8	Change input to Line 7 (input 7)
116	9	Change input to Line 8 (input 8)
116	10	Go to next input (input -)
116	11	Go to previous input (input +)
116	12	Toggle Standby/Operate
200	13	Toggle Mute/Unmute
116	14	Info (go to Status screen)
116	15	Cycle through display intensities (low/medium/high)
200	16	Volume up (volume +)
200	17	Volume down (volume -)
116	18	THX
116	19	Toggle Dolby Late Night Compression
116	20	Zone (go to Zone Control screen)
116	21	Trim (go to System Trims screen)
200	56	Function key F1
200	57	Function key F2
116	68	Mode (go to Mode Select screen)
116	84	Menu
116	85	Home
116	88	Step up (navigate up, +)
116	89	Step down (navigate down, -)
116	90	Step left (navigate left)
116	91	Step right (navigate right)
116	92	Enter
116	120	Change input to Line 9 (input 9)

116	121	Change input to Line 10 (input 10)
116	122	Change input to Line 11 (input 11, 7.1 input)
116	123	Change input to Line 12 (input 12, tape monitor)
200	134	Function key F3
200	135	Function key F4
116	145	Set Zone Mute mode on (zone mute)
116	146	Set Zone Mute mode off (zone unmute)
116	147	Toggle Zone Mute
116	148	Zone volume up (zone volume +)
116	149	Zone volume down (zone volume -)
116	150	Set unit in Operate (turn unit on)
116	151	Set unit in Standby (turn unit off)
200	152	Set Mute mode on (mute)
200	153	Set Mute mode off (unmute)
116	154	Set Tape Monitor on
116	155	Set Tape Monitor off
116	156	Set THX mode on (THX on)
116	157	Set THX mode off (THX off)
116	160	Set Dolby Late Night Compression on (Night on)
116	161	Set Dolby Late Night Compression off (Night off)
116	162	Trim front L/R (go to Level Trims – L/R Balance screen)
116	163	Trim center (go to Level Trims – Center screen)
116	164	Trim surround L/R (go to Level Trims – Surround screen)
116	165	Trim sub (go to Level Trims – Subwoofer screen)
116	169	Change Zone Input to Line 1 (input 1)
116	170	Change Zone Input to Line 2 (input 2)
116	171	Change Zone Input to Line 3 (input 3)
116	172	Change Zone Input to Line 4 (input 4)
116	173	Change Zone Input to Line 5 (input 5)
116	174	Change Zone Input to Line 6 (input 6)
116	175	Change Zone Input to Line 7 (input 7)
116	176	Change Zone Input to Line 8 (input 8)
116	177	Change Zone Input to Line 9 (input 9)
116	178	Change Zone Input to Line 10 (input 10)
116	179	Change Zone Input to Line 11 (input 11, 7.1 input)
116	180	Change Zone Input to Line 12 (input 12, tape monitor)
116	185	Switch to Listening Position 1
116	186	Switch to Listening Position 2
116	187	Switch to Listening Position 3

116	188	Switch to Listening Position 4
116	193	Change to mode 1 (multichannel)
116	194	Change to mode 2 (multichannel+THX)
116	195	Change to mode 3 (Dolby Pro Logic)
116	196	Change to mode 4 (Dolby Pro Logic+THX)
116	198	Change to mode 6 (music mode natural)
116	199	Change to mode 7 (music mode party)
116	204	Change to mode 12 (mono)
116	205	Change to mode 13 (mono+THX)
116	207	Change to mode 15 (surround 6.1)
116	208	Change to mode 16 (stereo)
116	209	Change to mode 17 (stereo+THX)
116	210	Change to mode 18 (Dolby Pro Logic II Movie)
116	211	Change to mode 19 (Dolby Pro Logic II Movie+THX)
116	212	Change to mode 20 (Dolby Pro Logic II Music)
116	228	Change to mode 24 (Dolby Digital EX)
116	229	Change to mode 25 (THX Music)
116	230	Change to mode 26 (THX Ultra2 Cinema)
116	231	Change to mode 27 (THX Surround EX)
116	232	Change to mode 28 (DTS Neo:6)
116	233	Change to mode 29 (DTS Neo:6+THX)
116	234	Change to mode 30 (DTS Neo:6 Cinema)
116	235	Change to mode 31 (DTS Neo:6 Cinema+THX)
116	236	Change to mode 32 (DTS Neo:6 Music)
116	237	Change to mode 33 (DTS Matrix 6.1)
116	238	Change to mode 34 (DTS Matrix 6.1+THX)
116	239	Change to mode 35 (stereo 24/96)

# SSP-300/600 HEX CODES

*RC6 MODE 0, SYSTEM CODE 116*

<b>IR CODE 1 TOGGLE 0</b>	<b>TAPE MONITOR ON/OFF</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275	
<b>IR CODE 1 TOGGLE 1</b>	<b>TAPE MONITOR ON/OFF</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275	
<b>IR CODE 2 TOGGLE 0</b>	<b>INPUT 1</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
<b>IR CODE 2 TOGGLE 1</b>	<b>INPUT 1</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
<b>IR CODE 3 TOGGLE 0</b>	<b>INPUT 2</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275	
<b>IR CODE 3 TOGGLE 1</b>	<b>INPUT 2</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275	
<b>IR CODE 4 TOGGLE 0</b>	<b>INPUT 3</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 4 TOGGLE 1</b>	<b>INPUT 3</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 5 TOGGLE 0</b>	<b>INPUT 4</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275	
<b>IR CODE 5 TOGGLE 1</b>	<b>INPUT 4</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275	
<b>IR CODE 6 TOGGLE 0</b>	<b>INPUT 5</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 6 TOGGLE 1</b>	<b>INPUT 5</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 7 TOGGLE 0</b>	<b>INPUT 6</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
<b>IR CODE 7 TOGGLE 1</b>	<b>INPUT 6</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
<b>IR CODE 8 TOGGLE 0</b>	<b>INPUT 7</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C	
<b>IR CODE 8 TOGGLE 1</b>	<b>INPUT 7</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C	
<b>IR CODE 9 TOGGLE 0</b>	<b>INPUT 8</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	

SSP-300/600 HEX CODES

<b>IR CODE 9 TOGGLE 1</b>	<b>INPUT 8</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275	
<b>IR CODE 10 TOGGLE 0</b>	<b>INPUT UP</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 125C	
<b>IR CODE 10 TOGGLE 1</b>	<b>INPUT UP</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 125C	
<b>IR CODE 11 TOGGLE 0</b>	<b>INPUT DOWN</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275	
<b>IR CODE 11 TOGGLE 1</b>	<b>INPUT DOWN</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275	
<b>IR CODE 12 TOGGLE 0</b>	<b>STANDBY/OPERATE</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 12 TOGGLE 1</b>	<b>STANDBY/OPERATE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 14 TOGGLE 0</b>	<b>INFO</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C	
<b>IR CODE 14 TOGGLE 1</b>	<b>INFO</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 15 TOGGLE 0</b>	<b>DISPLAY STEP TOGGLE</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	
<b>IR CODE 15 TOGGLE 1</b>	<b>DISPLAY STEP TOGGLE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	
<b>IR CODE 18 TOGGLE 0</b>	<b>THX</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C	
<b>IR CODE 18 TOGGLE 1</b>	<b>THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C	
<b>IR CODE 19 TOGGLE 0</b>	<b>DOLBY LATE NIGHT TOGGLE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 1275	
<b>IR CODE 19 TOGGLE 1</b>	<b>DOLBY LATE NIGHT TOGGLE</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 1275	
<b>IR CODE 20 TOGGLE 0</b>	<b>ZONE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 20 TOGGLE 1</b>	<b>ZONE</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 21 TOGGLE 0</b>	<b>TRIM</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 1275	

SSP-300/600 HEX CODES

<b>IR CODE 21 TOGGLE 1</b>	<b>TRIM</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 1275	
<b>IR CODE 68 TOGGLE 0</b>	<b>MODE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 68 TOGGLE 1</b>	<b>MODE</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 84 TOGGLE 0</b>	<b>MENU</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 84 TOGGLE 1</b>	<b>MENU</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 85 TOGGLE 0</b>	<b>HOME</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 0031 0032 1275	
<b>IR CODE 85 TOGGLE 1</b>	<b>HOME</b>
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 1275	
<b>IR CODE 88 TOGGLE 0</b>	<b>CURSOR UP</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0019 125C	
<b>IR CODE 88 TOGGLE 1</b>	<b>CURSOR UP</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0019 125C	



SSP-300/600 HEX CODES

<b>IR CODE 89 TOGGLE 0</b>	<b>CURSOR DOWN</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 89 TOGGLE 1</b>	<b>CURSOR DOWN</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 90 TOGGLE 0</b>	<b>CURSOR LEFT</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 90 TOGGLE 1</b>	<b>CURSOR LEFT</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 91 TOGGLE 0</b>	<b>CURSOR RIGHT</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 91 TOGGLE 1</b>	<b>CURSOR RIGHT</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 92 TOGGLE 0</b>	<b>ENTER</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 92 TOGGLE 1</b>	<b>ENTER</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 120 TOGGLE 0</b>	<b>INPUT 9</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 120 TOGGLE 1</b>	<b>INPUT 9</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
<b>IR CODE 121 TOGGLE 0</b>	<b>INPUT 10</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 121 TOGGLE 1</b>	<b>INPUT 10</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 122 TOGGLE 0</b>	<b>INPUT 11</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 122 TOGGLE 1</b>	<b>INPUT 11</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 123 TOGGLE 0</b>	<b>INPUT 12</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 123 TOGGLE 1</b>	<b>INPUT 12</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 145 TOGGLE 0</b>	<b>ZONE MUTE ON</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	
<b>IR CODE 145 TOGGLE 1</b>	<b>ZONE MUTE ON</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	

SSP-300/600 HEX CODES

<b>IR CODE 146 TOGGLE 0</b>	<b>ZONE MUTE OFF</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C	
<b>IR CODE 146 TOGGLE 1</b>	<b>ZONE MUTE OFF</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C	
<b>IR CODE 147 TOGGLE 0</b>	<b>ZONE MUTE TOGGLE</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 1275	
<b>IR CODE 147 TOGGLE 1</b>	<b>ZONE MUTE TOGGLE</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 1275	
<b>IR CODE 148 TOGGLE 0</b>	<b>ZONE VOLUME UP</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 148 TOGGLE 1</b>	<b>ZONE VOLUME UP</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 149 TOGGLE 0</b>	<b>ZONE VOLUME DOWN</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0031 0032 1275	
<b>IR CODE 149 TOGGLE 1</b>	<b>ZONE VOLUME DOWN</b>
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0031 0032 1275	
<b>IR CODE 150 TOGGLE 0</b>	<b>OPERATE</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 150 TOGGLE 1</b>	<b>OPERATE</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C	
<b>IR CODE 151 TOGGLE 0</b>	<b>STANDBY</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275	
<b>IR CODE 151 TOGGLE 1</b>	<b>STANDBY</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275	
<b>IR CODE 154 TOGGLE 0</b>	<b>TAPE MONITOR ON</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 154 TOGGLE 1</b>	<b>TAPE MONITOR ON</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 155 TOGGLE 0</b>	<b>TAPE MONITOR OFF</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 155 TOGGLE 1</b>	<b>TAPE MONITOR OFF</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 156 TOGGLE 0</b>	<b>THX ON</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 125C	
<b>IR CODE 156 TOGGLE 1</b>	<b>THX ON</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 157 TOGGLE 0</b>	<b>THX OFF</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 1275	
<b>IR CODE 157 TOGGLE 1</b>	<b>THX OFF</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 1275	
<b>IR CODE 160 TOGGLE 0</b>	<b>DOLBY LATE NIGHT MODE ON</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 160 TOGGLE 1</b>	<b>DOLBY LATE NIGHT MODE ON</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 161 TOGGLE 0</b>	<b>DOLBY LATE NIGHT MODE OFF</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 1275	
<b>IR CODE 161 TOGGLE 1</b>	<b>DOLBY LATE NIGHT MODE OFF</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 1275	
<b>IR CODE 162 TOGGLE 0</b>	<b>TRIM FRONT L/R</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0019 125C	
<b>IR CODE 162 TOGGLE 1</b>	<b>TRIM FRONT L/R</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0031 0019 125C	
<b>IR CODE 163 TOGGLE 0</b>	<b>TRIM CENTER</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0019 0019 1275	

SSP-300/600 HEX CODES

<b>IR CODE 163 TOGGLE 1</b>	<b>TRIM CENTER</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0032 0019 0019 1275	
<b>IR CODE 164 TOGGLE 0</b>	<b>TRIM SURROUND L/R</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 164 TOGGLE 1</b>	<b>TRIM SURROUND L/R</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 165 TOGGLE 0</b>	<b>TRIM SUB</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0032 1275	
<b>IR CODE 165 TOGGLE 1</b>	<b>TRIM SUB</b>
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0032 0031 0032 1275	
<b>IR CODE 169 TOGGLE 0</b>	<b>ZONE INPUT 1</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0032 1275	
<b>IR CODE 169 TOGGLE 1</b>	<b>ZONE INPUT 1</b>
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0032 1275	
<b>IR CODE 170 TOGGLE 0</b>	<b>ZONE INPUT 2</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0031 0032 0031 0019 125C	
<b>IR CODE 170 TOGGLE 1</b>	<b>ZONE INPUT 2</b>
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0031 0032 0031 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 171 TOGGLE 0</b>	<b>ZONE INPUT 3</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0031 0032 0019 0019 1275	
<b>IR CODE 171 TOGGLE 1</b>	<b>ZONE INPUT 3</b>
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0031 0032 0019 0019 1275	
<b>IR CODE 172 TOGGLE 0</b>	<b>ZONE INPUT 4</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 172 TOGGLE 1</b>	<b>ZONE INPUT 4</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0032 0019 0019 125C	
<b>IR CODE 173 TOGGLE 0</b>	<b>ZONE INPUT 5</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0032 0032 1275	
<b>IR CODE 173 TOGGLE 1</b>	<b>ZONE INPUT 5</b>
0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0032 0032 1275	
<b>IR CODE 174 TOGGLE 0</b>	<b>ZONE INPUT 6</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0019 0019 0032 0019 125C	
<b>IR CODE 174 TOGGLE 1</b>	<b>ZONE INPUT 6</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0019 0019 0032 0019 125C	
<b>IR CODE 175 TOGGLE 0</b>	<b>ZONE INPUT 7</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0019 0019 0019 1275	

SSP-300/600 HEX CODES

<b>IR CODE 175 TOGGLE 1</b>	<b>ZONE INPUT 7</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0032 0019 0019 0019 0019 0019 0019 1275	
<b>IR CODE 176 TOGGLE 0</b>	<b>ZONE INPUT 8</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 176 TOGGLE 1</b>	<b>ZONE INPUT 8</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 177 TOGGLE 0</b>	<b>ZONE INPUT 9</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0032 1275	
<b>IR CODE 177 TOGGLE 1</b>	<b>ZONE INPUT 9</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 0032 1275	
<b>IR CODE 178 TOGGLE 0</b>	<b>ZONE INPUT 10</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 0031 0019 125C	
<b>IR CODE 178 TOGGLE 1</b>	<b>ZONE INPUT 10</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 0031 0019 125C	
<b>IR CODE 179 TOGGLE 0</b>	<b>ZONE INPUT 11</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 0019 0019 1275	
<b>IR CODE 179 TOGGLE 1</b>	<b>ZONE INPUT 11</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 0019 0019 1275	



SSP-300/600 HEX CODES

<b>IR CODE 180 TOGGLE 0</b>	<b>ZONE INPUT 12</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 0019 0019 125C	
<b>IR CODE 180 TOGGLE 1</b>	<b>ZONE INPUT 12</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 0019 0019 125C	
<b>IR CODE 185 TOGGLE 0</b>	<b>CONFIGURATION 1</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 185 TOGGLE 1</b>	<b>CONFIGURATION 1</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 186 TOGGLE 0</b>	<b>CONFIGURATION 2</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 186 TOGGLE 1</b>	<b>CONFIGURATION 2</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0031 0019 125C	
<b>IR CODE 187 TOGGLE 0</b>	<b>CONFIGURATION 3</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 187 TOGGLE 1</b>	<b>CONFIGURATION 3</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0019 0019 1275	
<b>IR CODE 188 TOGGLE 0</b>	<b>CONFIGURATION 4</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 188 TOGGLE 1</b>	<b>CONFIGURATION 4</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 193 TOGGLE 0</b>	<b>MODE 1: MULTICHANNEL</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275	
<b>IR CODE 193 TOGGLE 1</b>	<b>MODE 1: MULTICHANNEL</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275	
<b>IR CODE 194 TOGGLE 0</b>	<b>MODE 2: MULTICHANNEL + THX</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C	
<b>IR CODE 194 TOGGLE 1</b>	<b>MODE 2: MULTICHANNEL + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0032 0031 0019 125C	
<b>IR CODE 195 TOGGLE 0</b>	<b>MODE 3: DOLBY PRO LOGIC</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275	
<b>IR CODE 195 TOGGLE 1</b>	<b>MODE 3: DOLBY PRO LOGIC</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 1275	
<b>IR CODE 196 TOGGLE 0</b>	<b>MODE 4: DOLBY PRO LOGIC + THX</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 196 TOGGLE 1</b>	<b>MODE 4: DOLBY PRO LOGIC + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0032 0031 0019 0019 0019 125C	

SSP-300/600 HEX CODES

<b>IR CODE 198 TOGGLE 0</b>	<b>MODE 6: MUSIC MODE NATURAL</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 198 TOGGLE 1</b>	<b>MODE 6: MUSIC MODE NATURAL</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 199 TOGGLE 0</b>	<b>MODE 7: MUSIC MODE PARTY</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
<b>IR CODE 199 TOGGLE 1</b>	<b>MODE 7: MUSIC MODE PARTY</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 1275	
<b>IR CODE 204 TOGGLE 0</b>	<b>MODE 12: MONO</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 204 TOGGLE 1</b>	<b>MODE 12: MONO</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 205 TOGGLE 0</b>	<b>MODE 13: MONO + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0032 0032 1275	
<b>IR CODE 205 TOGGLE 1</b>	<b>MODE 13: MONO + THX</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0032 0032 1275	
<b>IR CODE 207 TOGGLE 0</b>	<b>MODE 15: SURROUND 6.1</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	

SSP-300/600 HEX CODES

<b>IR CODE 207 TOGGLE 1</b>	<b>MODE 15: SURROUND 6.1</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 0019 1275	
<b>IR CODE 208 TOGGLE 0</b>	<b>MODE 16: STEREO</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 208 TOGGLE 1</b>	<b>MODE 16: STEREO</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 209 TOGGLE 0</b>	<b>MODE 17: STEREO + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 1275	
<b>IR CODE 209 TOGGLE 1</b>	<b>MODE 17: STEREO + THX</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 1275	
<b>IR CODE 210 TOGGLE 0</b>	<b>MODE 18: DOLBY PRO LOGIC II MOVIE</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 125C	
<b>IR CODE 210 TOGGLE 1</b>	<b>MODE 18: DOLBY PRO LOGIC II MOVIE</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 125C	
<b>IR CODE 211 TOGGLE 0</b>	<b>MODE 19: DOLBY PRO LOGIC II MOVIE + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 1275	
<b>IR CODE 211 TOGGLE 1</b>	<b>MODE 19: DOLBY PRO LOGIC II MOVIE + THX</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 1275	

SSP-300/600 HEX CODES

<b>IR CODE 212 TOGGLE 0</b>	<b>MODE 20: DOLBY PRO LOGIC II MUSIC</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 212 TOGGLE 1</b>	<b>MODE 20: DOLBY PRO LOGIC II MUSIC</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0031 0032 0031 0019 0019 0019 125C	
<b>IR CODE 228 TOGGLE 0</b>	<b>MODE 24: DOLBY DIGITAL EX</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 228 TOGGLE 1</b>	<b>MODE 24: DOLBY DIGITAL EX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 125C	
<b>IR CODE 229 TOGGLE 0</b>	<b>MODE 25: THX MUSIC</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0031 0032 1275	
<b>IR CODE 229 TOGGLE 1</b>	<b>MODE 25: THX MUSIC</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0031 0032 1275	
<b>IR CODE 230 TOGGLE 0</b>	<b>MODE 26: THX ULTRA2 CINEMA</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 230 TOGGLE 1</b>	<b>MODE 26: THX ULTRA2 CINEMA</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 231 TOGGLE 0</b>	<b>MODE 27: THX SURROUND EX</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 1275	

SSP-300/600 HEX CODES

<b>IR CODE 231 TOGGLE 1</b>	<b>MODE 27: THX SURROUND EX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 1275	
<b>IR CODE 232 TOGGLE 0</b>	<b>MODE 28: DTS NEO:6</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 125C	
<b>IR CODE 232 TOGGLE 1</b>	<b>MODE 28: DTS NEO:6</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 125C	
<b>IR CODE 233 TOGGLE 0</b>	<b>MODE 29: DTS NEO:6 + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 1275	
<b>IR CODE 233 TOGGLE 1</b>	<b>MODE 29: DTS NEO:6 + THX</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 1275	
<b>IR CODE 234 TOGGLE 0</b>	<b>MODE 30: DTS NEO:6 CINEMA</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0032 0031 0019 125C	
<b>IR CODE 234 TOGGLE 1</b>	<b>MODE 30: DTS NEO:6 CINEMA</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0032 0031 0019 125C	
<b>IR CODE 235 TOGGLE 0</b>	<b>MODE 31: DTS NEO:6 CINEMA + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0032 0019 0019 1275	
<b>IR CODE 235 TOGGLE 1</b>	<b>MODE 31: DTS NEO:6 CINEMA + THX</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0032 0019 0019 1275	

SSP-300/600 HEX CODES

<b>IR CODE 236 TOGGLE 0</b>	<b>MODE 32: DTS NEO:6 MUSIC</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 236 TOGGLE 1</b>	<b>MODE 32: DTS NEO:6 MUSIC</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0019 0019 0019 125C	
<b>IR CODE 237 TOGGLE 0</b>	<b>MODE 33: DTS MATRIX 6.1</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0032 1275	
<b>IR CODE 237 TOGGLE 1</b>	<b>MODE 33: DTS MATRIX 6.1</b>
0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0032 1275	
<b>IR CODE 238 TOGGLE 0</b>	<b>MODE 34: DTS MATRIX 6.1 + THX</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0019 125C	
<b>IR CODE 238 TOGGLE 1</b>	<b>MODE 34: DTS MATRIX 6.1 + THX</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0032 0019 125C	
<b>IR CODE 239 TOGGLE 0</b>	<b>MODE 35: STEREO 24/96</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0019 1275	
<b>IR CODE 239 TOGGLE 1</b>	<b>MODE 35: STEREO 24/96</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 0019 0019 1275	

*RC6 MODE 0, SYSTEM CODE 200*

<b>IR CODE 13 TOGGLE 0</b>	<b>MUTE TOGGLE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275	
<b>IR CODE 13 TOGGLE 1</b>	<b>MUTE TOGGLE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275	
<b>IR CODE 16 TOGGLE 0</b>	<b>VOLUME UP</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 16 TOGGLE 1</b>	<b>VOLUME UP</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 125C	
<b>IR CODE 17 TOGGLE 0</b>	<b>VOLUME DOWN</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	
<b>IR CODE 17 TOGGLE 1</b>	<b>VOLUME DOWN</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 1275	
<b>IR CODE 56 TOGGLE 0</b>	<b>F1</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	
<b>IR CODE 56 TOGGLE 1</b>	<b>F1</b>
0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C	



SSP-300/600 HEX CODES

<b>IR CODE 57 TOGGLE 0</b>	<b>F2</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 57 TOGGLE 1</b>	<b>F2</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275	
<b>IR CODE 134 TOGGLE 0</b>	<b>F3</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 134 TOGGLE 1</b>	<b>F3</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C	
<b>IR CODE 135 TOGGLE 0</b>	<b>F4</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
<b>IR CODE 135 TOGGLE 1</b>	<b>F4</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275	
<b>IR CODE 152 TOGGLE 0</b>	<b>MUTE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 125C	
<b>IR CODE 152 TOGGLE 1</b>	<b>MUTE</b>
0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0019 125C	
<b>IR CODE 153 TOGGLE 0</b>	<b>UNMUTE</b>
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275	

SSP-300/600 HEX CODES

IR CODE 153 TOGGLE 1	UNMUTE
0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275	