

M1

B&W

Bowers & Wilkins



At the heart of Mini Theatre is the M-1. Small it may be, but the M-1 is brimming with innovative acoustic engineering. From the inside out, it has been conceived as a unified system delivering superlative sound, looks and ease of use. Starting on a blank sheet of paper, its design has evolved in a totally integrated way, from the tube-loaded tweeter and woven bass driver cone to the two-piece cabinet and concealed cabling.

Put an M-1 in all five satellite speaker positions alongside a B&W subwoofer and you'll have a sum of parts that is movie magic in the making.

Description: 2-way vented-box system
Frequency range (-6dB): 72Hz and 50kHz
Recomm.amp. power: 20W – 100W into 8Ω on unclipped programme
Sensitivity: 85dB spl (2.83V, 1m)

Impedance: 8Ω (minimum 4.8Ω)
Dimensions: H 243mm W 114mm D 172mm
H 9.6 W 4.9 D 6.8"
Weight: 3.6kg / 8 lbs.