

*Classé*

Omega SACD-1



**Model** Omega SACD-1

**Analogue section**

Balanced/Single-ended output (SACD) 1.2V  
Balanced/Single-ended output (CD) 2V  
Frequency response 20-20.000Hz

**Power supply**

Transformer size 55VA  
Number of capacitors 18  
Total capacitance 84,600µF

**Digital section**

D/A converter Crystal  
CS4397x6  
24/96 up-sampling Yes  
AES/EBU output 1x  
Coaxial output 2x  
Optical Tos-Link 1x  
ST Glass 1x

**Software support**

CD Yes  
CDR Yes  
CDRW Yes  
SACD Yes  
HDCD Yes

**Weight & measurements**

Net weight 23kg  
50.7lbs  
Height 137mm  
5.4"  
Width 464mm  
18.25"  
Depth 394mm  
15.5"

**Power supply**

Net weight 4.5kg  
9.9lbs  
Height 102mm  
4"  
Width 241mm  
9.5"  
Depth 381mm  
15"

Classe Audio Inc. reserve  
the right to amend technical  
specifications without further  
notice.

**USA & Canada**

Classe Audio Inc.  
5070 Francois-Cusson  
Lachine  
Quebec  
Canada  
H8T 1B3

Telephone +1 514 636 6384  
Facsimile +1 514 636 1428  
www.classe.com  
cservice@classeaudio.com

**Europe**

B&W Loudspeakers Ltd  
Meadow Road  
Worthing BN11 2RX  
England

**UK**

B&W Loudspeakers (UK) Ltd  
Marlborough Road  
Lancing BN15 8TR

Telephone +44 1903 750750  
Facsimile +44 1903 750694  
uksales@bwspeakers.com

**Hong Kong**

B&W Loudspeakers (Asia) Ltd  
Flat U, 11F Camelpoint Building  
Block 111, 60 Hoi Yuen Road  
Kwun Tong, Kowloon  
Hong Kong

Telephone +8522 790 8903  
Facsimile +8522 341 2777  
bwahome@bwspeakerasia.com.hk

Design:  
Thomas Manss & Company

PU08419

